

**Features:**

- Remote control and get meter data by Bluetooth 5.0 Technology.
- Set schedule: Turn the connected lights and electrical devices on or off by schedule.
- Energy monitoring: Track voltage, current, WH (Watt-Hour), and analyze the real-time and historical power consumption of connected devices.
- OLED display panel: Intuitive way to display power consumption status.
- Scenes setting: Set the time to switch lights and devices on and off while out. It looks like someone being at home.
- OEM/ODM Solutions: Provide high quality power meter plug under your brand.

SPECIFICATION

Model	EM-P1P2-BLE-OLED
Connection	Bluetooth 5.0
Input voltage Range	AC 90-240V
Load Current	15A
Output Power	1500W
Connection range*	20 m
Measurement and Precision	AC Voltage 1%
	AC Current 1%
	AC Active Power 1%
	Frequency 0.2%
	Cumulative Watt per Hour <2%
Max. Power Consumption	< 0.9W
Standby Power Consumption	≅ 0.4 W
Operating temperature	-10°C~50°C
Operating humidity	20%~85% RH
Display panel size	0.96 inch (24mm) OLED
Dimensions	L85x W43.95 x H38 mm
Colors	Grey White, Black
Weight	94g
Warranty	1 year
APP Support	Android/ iOS

*The connection range may increase or decrease depending on the environment,